

Mergeable Settings

The table below shows the configuration entries for which changes can be merged and those that require a system reboot. The Send Configuration menu shown when sending a configuration to the IP Office automatically indicates when the configuration is mergeable.

Mergeable	3.2+	Pre-3.2
System	-	-
- System	✓*1	✗
- LAN1/LAN2	✗	✗
- DNS	✗	✗
- Voicemail	✓*2	✗
- Telephony	✓*3	✗
- VoIP	✗	✗
- LDAP	✗	✗
- System Events	✗	✗
- CDR/SMDR	✓	✗
- Trunking	✓	-
Line	✗	✗
Control Unit	✗	✗
Extension	✗	✗*4
User	✓	✓
Hunt Group	✓	✓
Short Code	✓	✓
Service	✓	✓
RAS	✓	✓
Incoming Call Route	✓	✓

Mergeable	3.2+	Pre-3.2
WAN Port	✗	✗
Directory	✓	✓
Time Profile	✓	✗
Firewall Profile	✓	✓
IP Route	✓	✓
Least Cost Route	✓	✓
Account Code	✓	✓
License	✓	✓
Tunnel	✗	✗
Logical LAN	✗	✗
Wireless	✗	✗
User Rights	✓	✓
Auto Attendant	✓	✗
Authorization Code	✓	✗
ARS	✓	-
E911 System	✗	✗

- ***1 - 3.2+ | System | System**
Changes to Locale, License Server IP Address and Favor RIP Routes over Static require a reboot.
- ***2 - 3.2+ | System | Voicemail**
Changes to Voicemail Type require a reboot.
- ***3 - 3.2+ | System | Telephony**
Changes to Companding LAW and Busy Tone Detection require a reboot.
- ***4 - 4.1+ | Extension**
For IP Office 4.1+, Base Extension and Disable Speakerphone are mergeable.

2/22/2010

IP Office Knowledge Base

freedom from patent or any other protective rights of Avaya or others.

All trademarks identified by (R) or TM are registered trademarks or trademarks respectively of Avaya Inc. All other trademarks are the property of their respective owners.

http://marketingtools.avaya.com/knowledgebase/businesspartner/ipoffice/mergedProjects/manager/html_mergeable_settings.htm

Last Modified: 21/01/2009